

TX150 Line Card Updater Instructions

STEP 1.

Make sure you have at least version v1.1 of the TX150 application.

III TX150 v1.1 File Setup Help



150 CABLE MAPPER

STEP 2

Connect up a TC150 to the laptop and connect a Link Cable to the Line Card that requires firmware update.

STEP 3

Using File Explorer, go to C:\Program Files (x86)\Teletech\TX150

	ch\TX150							_		×
File Home Share View										^ ?
Image: Pin to Quick access Copy Paste Cut Paste shortcut	Move Copy to * Cot Delete Rename	New item ▼ 1 Easy access ▼ 1 folder	Properties	Edit ∰ History	Select all Select none	ion				
Clipboard	Organize	New	0	pen	Select					
← → × ↑ 📙 > This PC → Local Dis	c (C:) → Program Files (x86) → Tele	tech → TX150 →					~	ට Search TX15	0	Q
Free RAR Extract Frog	Name ^	Date modi	fied	Туре	Size					
	extras	30/06/2016	5 5:55 PM	File folder						
FreeSmith	platforms	30/06/2016	5 5:55 PM	File folder						
Google	CardUpdater.exe	4/08/2016	12:02 PM	Application	34	40 KB				
GPLGS	concrt140.dll	Date created: 4/08/2016 12:1	1 PM	Application ext	tens 24	40 KB				
Hewlett-Packard	itd2xx.dll	Size: 339 KB		Application ext	tens 26	58 KB				
HP	msvcp140.dll	5/11/2015	11:54 PM	Application ext	tens 43	33 KB				
	Qt5Core.dll	30/05/2016	5 5:17 PM	Application ext	tens 4,53	30 KB				

Doubler click on the file, CardUpdater.exe. The following box will open.

CardUpdater	_	×
Controls		
Connec	t to controller	
Upo	date card	

Click on the button, Connect to controller.

CardUpdater	_		\times
Controls			
Connec	t to controlle	20	
Up	date card		

The button Connect to controller will be disabled and the Update card button enabled. With the target Line Card connected to the TU150 controller, click on the button, Update card.

CardUpdater	_	×
Controls		
Connect to	controller	
Updat	e card	

The CardUpdater, detects the serial number of the Line Card and also the style (in the below case; serial 2620078 and an R&M16. Wait approximately 40 seconds and...



The program will produce the following output and the LED on the Line Card will light up green.

CardUpdater	-		×				
Controls							
Connect to c	ontroller						
Update o	Update card						
Detected R&M VS Compact serialNumber 2620078 Loading firmware - please w New firmware installed OK Updating bootloader Finished.	(Splitters) ait	16 pair					

Disconnect the Line Card and connect the next Line Card. Repeat the above process of clicking on the button, Update card. The following messages will appear. In the following examples, serial numbers, 2620078; 2620079 and 2620080 have been updated or are in the process of updating.

🔝 CardUpdater —	. [×		
Controls					
Connect to control	er				
Update card				CardUpdater — 🗆	\times
Detected R&M VS Compact (Splitte serialNumber 2620078	ers) 16 p	pair		ntrols	
Loading firmware - please wait New firmware installed OK				Connect to controller	
Updating bootloader Finished.	1.10			Update card	
serialNumber 2620079 Loading firmware - please wait	ers) 16 p	pair)ading firmware - please wait Cew firmware installed OK	^
				pdating bootloader nished.	
				etected R&M VS Compact (Splitters) 16 pair rialNumber 2620079	
				ew firmware - please wait ew firmware installed OK	
				rinished. Detected R&M VS Compact (Splitters) 16 pair	
				serialNumber 2620080 Loading firmware - please wait	
					~

Copyright Teletech Pty. Ltd. 2016.

Document Version 1.0





Quality ISO 9001 €SAI GLOBAL

Innovation Solutions for the telecommunications industry