Increase efficiency in the telecommunications race



The TX150 automates the process of proving the end-to-end terminations of cables after installation. The TX150 is ideal for checking and hand-over of tie cables for FTTN, FTTB and cables in high rise or large buildings. Used for bare cable (cables not yet connected to any services).

Simple steps to better cable verification

- At one end Set-up the Line Cards and connect the TX150 Controller and laptop
- Move to the other end. Set-up the Line Cards and connect the TX150 Controller and laptop
- Press Start the results are displayed within 3 seconds – All pairs are checked and identified.

Benefits of TX150 Cable Mapper

- Big time saver very, very fast operation
- Simple to use
- Single person operation
- Instant feedback for installation staff to improve cabling quality
- Removes re-visits and debate about hand-over quality

Teletech

Using a multi-meter for continuity checking is now so last century

The TX150 instantly detects cabling errors

- Pair connections
- Split pairs
- Inverted A/B
- Open Circuits
- Short circuits

TX150	v1.5.0									- U	
File Setup Help											
70	detect	TX150		E MAPPER	LAT	LONG		Date	Time		
Istener Exchange Istener Start Pair Istener Street Istener Street									C		
Start Pause Save Start Time: 10:53:40 Elapsed Time: 0min Start Pause LISTENER X @ CO_LAYOUT Normal											
	ĭ	2	3	4	5	6	7	8	9	10	
51-60	B52/A52	B51/A51	B54/A53	B53/A54	B55/A55	B56/A56	B57/A	57 B58/A58	B59/A59	60	
41-50	41	42	43	44	45	46	47	48	49	50	
31-40	31	32	33	34	35	36	37	38	39	40	
21-30	21	22	23	24	25	26	27	28	29	30	
11-20	11	12	13	14	15	16	17	18	19	20	
1-10	1	2	3	4	5	6	7	8	9	10	

A full range of Line Card connectors are available – for any job



Technical Specifications

Line Card (plugs into connector blocks)								
TYPES:	Krone LSA 10-pair; Krone HD180 10-pair; 3M 20-pair; Quante 10-pair; Quante 20-pair;							
	R&M 10-pair; R&M 16-pair; R&M 20-pair							
PAIRs per CONTROLLER	Over 600 pairs (eg. 30x20 pair Line Cards to 60x10 pair Line Cards)							
Operating Distance	0 to 400m cable length between Line Cards							
Weight: 60 to 170g								
Dimensions: 75mm x 90mm x 15mm to 100mm x 170mm x 15mm								
Controller (controls Line Card) Image: Control s Line Card								
Battery	DC5V 1A	Certified						
Battery Chemistry	Lithium	Cert						
Battery Capacity	20 hours minimum operating between charges	Quality						
Weight: 330g (including battery and leads)								
Dimensions: 80mm x 120mm x 25mm								

Teletech

Innovative solutions for the telecommunications industry

Teletech Pty Ltd Unit 8, 2 Apollo Court Blackburn, Victoria 3130, Australia

Tel: +613 9877 3033, sales@teletech.com.au www.teletech.com.au